


SPECIFICATIONS

- ✓ Electromagnetic bolt NC* (Open while powered).
- ✓ The insert allows opening the bolt with a key during a power outage.
- ✓ Indication of door closed and opened status.
- ✓ Lockout to prevent activation when the door is in the wrong position.
- ✓ Protection against overvoltage and polarity reversal.
- ✓ Automatic locking.

TECHNICAL DATA



Current	12 V DC
startup current consumption.	850 mA for 12V DC
operating current	90 mA for 12V DC
durability	24000 N
adjustable closing delay.	0, 3, 6, 9 sec.